



Figures and illustrations in this User Manual are provided for reference only and may differ from actual product appearance. Model design and specifications may be changed without notice.

Important Warranty Information Regarding Television Format Viewing

See the warranty card for more information on warranty terms.

Wide screen format LED Displays (16:9), the aspect ratio of the screen width to height) are primarily designed to view wide screen format full-motion video. The images displayed on them should primarily be in the wide screen 16:9 ratio format, or expanded to fill the screen if your model offers this feature and the images are consistently moving. Displaying stationary graphics and images on screens, such as the disk labels on DVD, expanded standard format television video and programming, should be limited to no more than 5% of the total television viewing per week. Additionally, viewing other stationary images and text such as stock market reports, video game displays, station logos, web sites or computer graphics and patterns, should be limited as described above for all televisions. Displaying stationary images that exceed the above guidelines can cause uneven aging of LED Displays that have a built-in permanent burn-in or ghosting in the LED picture. To avoid this, vary the programming and images, and primarily display full screen moving images, not stationary patterns or dark bars. On LED models that offer picture framing features, use these controls to view other formats as full screen picture. Be careful in the selection and duration of television formats you use for viewing. Uneven LED aging as a result of format selection and use, as well as burn-in images, are not covered by your Samsung limited warranty.

For the location of a SAMSUNG Authorized Service Center, please call toll free: In the United States: 1-800-SAMSUNG (1-800-726-7864) In Canada: 1-800-SAMSUNG.

Still Image Warning

Avoid displaying still images (such as jpeg picture files) or still image elements (such as TV channel logos, TV shows or movies in panorama or 4:3 format, stock or news scroll bars, etc.) on the screen. The constant display of still pictures can cause ghosting or image burn in (image retention) on the LED screen, which will affect image quality. To reduce the risk of the effect, please follow the recommendations below: Always displaying the same TV channel for long periods. Always try to display any image in full screen mode. Use the TV's Picture Options menu to select the optimal screen size. Reduce brightness and contrast values to the minimum required to achieve the desired picture quality. Values that exceed the minimum may speed up the burn-in process. Frequently use all TV features designed to reduce image retention and screen burn-in. Refer to proper user manual section for details.

WARRANTY INFORMATION

Subject to the requirements, conditions, exclusions and limitations of the original Limited Warranty supplied with Samsung Electronics (SAMSUNG) products, and the requirements, conditions, exclusions and limitations contained herein, SAMSUNG will additionally provide Warranty Repair Services in the United States on SAMSUNG products purchased in Canada, and in Canada on SAMSUNG products purchased in the United States, for the warranty period originally specified, and to the Original Purchaser only.

The above described warranty repairs must be performed by a SAMSUNG Authorized Service Center. Along with this Statement, the Original Limited Warranty Statement and a dated Bill of Sale as Proof of Purchase must be presented to the Service Center.

Table with 3 columns: Country, Address, and Contact Info. Rows for Canada and USA.




© 2014 Samsung Electronics Co., Ltd. All rights reserved.

Timer Viewing

You can schedule a channel to be displayed automatically at a set time, even when you are watching another channel. You must set the current time first in the Time + Clock function to use Time Viewing.

To schedule a channel, follow these steps:

- 1. Select a channel in the Added Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Time Viewing in the Tools menu, and then press the ENTER button. The Time Viewing screen appears.



- 4. Use the Arrow buttons to move from entry field to entry field and the Arrow buttons to change the entries. When numbers are displayed, you can also enter numbers directly using the number keypad on your remote.
5. If you select Everyday or Every Week, the date you select in the Date field becomes the start date for your scheduled viewing. For Everyday, the TV will turn on every day, at the time you selected, starting from that date. For Every Week, the TV will turn on every week, on the same day of the week as the start date you selected, at the time you selected, from that day on, if you select Once, the TV will turn on once, on the date and time you selected.

Press the ENTER button on your remote when done.

Only Added Channels can be scheduled.

Scheduled programs and channels are displayed in the Programmed List.

When you select a digital channel, press the Arrow button to view the digital program list. If you highlight a program in the list, and then press the ENTER button, you can select Time Viewing for that program directly.

Select All: Select all the channels in the displayed channel list.

Deselect All: Deselect all the selected displayed channels.

You can only select Deselect All when one or more channels are selected.

Channel Name Edit: Select channels only. Lets you assign a name to live channels to an analog channel. For example, 16:1, Food, Golf, etc. This makes it easier to find and select a channel.

Auto Program: See Auto Program under Memorizing Channels.

The On Screen Menus

Your TV has two kinds of menus, the Main menu and the various Tools menus. The Main menu gives you access to most or all of the menu options available on your TV. The Tools menus display a selected number of frequently used menu options that change depending on the screen you are viewing. A Tools menu symbol (T) in the lower right side of the screen indicates that a Tools menu is available.

The Main menu has seven primary categories:

- Picture
Input
Application
Channel
Support
Setup

To view the Main menu, press the MENU button on your remote. To view the Tools menu, press the TOOLS button on your remote.

The menu options that appear in the Main menu depend on the Source you have selected. For example, if you have selected the HDMI source, the Channel category will not appear. To see the Channel category, you must first select TV in the Source List.

The Menu options are presented below, arranged by Main menu categories. A Tools button symbol (T) next to an option name indicates the option is also available in one of the Tools menus.

Picture Menu

Select your preferred picture mode.

- When your TV is connected to a PC, you can only select Entertain and Standard.
Dynamic: Brightens the screen. Suitable for a bright room.
Standard: Suitable for a normal.
Movie: Darkens the screen, making it less glossy. Suitable for watching movies in a darkened room.
Picture: Adjusts the White Balance to its default settings.
Gamma: Adjusts the primary color intensity.
Dynamic Contrast (Off / Low / Medium / High): Adjusts the screen contrast.
Black Tone (Off / Dark / Darker / Darkest): Selects the black level to adjust the screen depth. Darker settings make blacks look darker.
Flesh Tone: Adjusts the amount of red in skin tones.
Motion Lighting (Off / On): When on, the TV automatically adjusts the brightness of the screen in response to the brightness of the room. In bright light, the screen brightens. In dim light, the screen darkens.
Available in Standard mode only.

Backlight / Contrast / Brightness / Sharpness / Color / Tint (G/R)

- Backlight: Adjusts the brightness of the screen by adjusting the brightness of the individual pixels.
Contrast: Increases or decreases the contrast between dark and light areas of the picture.
Brightness: Adjusts the brightness of the screen. Not as effective as Backlight.
Sharpness: Sharpens or blurs the edges of objects.
Color: Adjusts the color saturation. The higher the Color setting is, the more intense the color. Low settings remove color and the picture becomes black, white and gray.
Tint: Adjusts the amount of green and red in the picture. As you increase the amount of green, the amount of red decreases and vice versa.
When the TV is connected to a PC, you can only make changes to Backlight, Contrast, Brightness, and Sharpness.

Advanced Settings

Available in Standard and Movie mode only. Compared to previous models, new Samsung TVs offer a more precise picture with more precise controls.
When your TV is connected to a PC, you can only make changes to Gamma and White Balance.
Color Space (Auto / Native): Auto automatically matches the range of colors available to create pictures to the color range of the video source. Native provides a color wider than the color range of the video source.
White Balance: Adjusts the color temperature of the picture so that white objects look white instead of, for example, slightly pink or slightly yellow and the overall color of the picture looks natural.
R-Offset / G-Offset / B-Offset: Adjusts each color's red, green, blue, darkness.
R-Gain / G-Gain / B-Gain: Adjusts each color's red, green, blue brightness.
Reset: Resets the White Balance to its default settings.
Gamma: Adjusts the primary color intensity.
Dynamic Contrast (Off / Low / Medium / High): Adjusts the screen contrast.
Black Tone (Off / Dark / Darker / Darkest): Selects the black level to adjust the screen depth. Darker settings make blacks look darker.
Flesh Tone: Adjusts the amount of red in skin tones.
Motion Lighting (Off / On): When on, the TV automatically adjusts the brightness of the screen in response to the brightness of the room. In bright light, the screen brightens. In dim light, the screen darkens.
Available in Standard mode only.

Picture Options

When the TV is connected to a PC, you can only make changes to the Color Tone, Size and HDMI Black Level.
Color Tone (Cool / Standard / Warm 1 / Warm 2): Cool makes the picture bluer (cooler). Warm 1 and Warm 2 make the picture warmer. Warm 1 and Warm 2 are deactivated when the picture mode is set to Dynamic.
Size: Set the size and aspect ratio of the picture on the screen. Your cable box or satellite receiver may have its own set of screen sizes as well. However, we highly recommend you use the TV's 16:9 mode most of the time.
Zoom: Provides moderate magnification of the picture. Sides, top, and bottom are cut off.
Wide Fit: Enlarges the aspect ratio of the picture so the picture fits the entire screen.
4:3: Sets the picture to the old, 4:3 format and puts black or gray borders on the right and left of the picture.
Do not watch your TV in the 4:3 format for a long time. Traces of borders displayed on the left, right and center of the screen may cause image retention (screen burn) which is not covered by the warranty.
Screen Fit: Displays the full image without any cut-off when your TV is inputting HDMI (720p / 1080i / 1080p) or Component (1080i / 1080p) HD signals.
HD (High Definition) has a 16:9 aspect ratio and 1080i/1080p (1920x1080) or 720p (1280x720) resolution.
You can adjust and store settings for each external device you have connected to an input on the TV. Picture Size available by Input Source are listed below.

Picture Settings

When the TV is connected to a PC, you can only make changes to the Color Tone, Size and HDMI Black Level.

- Standard: Selects the normal sound mode.
Music: Emphasizes bass notes.
Movie: Provides the best sound for movies.
Clear Voice: Emphasizes voices over other sounds.
Amplify: Increase the intensity of high-frequency sounds to allow a better listening experience for the hearing impaired.

Equalizer

- Balance L/R: Adjusts the balance between the right and left channels.
100Hz / 300Hz / 1KHz / 30KHz / 10KHz (Bandwidth Adjustment): Adjusts the loudness of specific bandwidth frequencies.
Reset: Resets the equalizer to its default settings.

SRS TruSurround HD (On/Off)

Available in Standard sound mode only.
SRS TruSurround HD is a patented SRS technology that solves the problem of playing 5.1 multichannel content through two speakers. TruSurround delivers a compelling, virtual surround sound experience through any two-speaker playback system, including in-ear television speakers. It is fully compatible with all multichannel formats.
When the TV is connected to a PC, you can only make changes to the Color Tone, Size and HDMI Black Level.
Input Source are listed below.

Preferred Language

Digital-TV broadcasts can transmit many audio tracks simultaneously (for example, simultaneous translations of a program into foreign languages).
You can only select a language from among the ones being broadcast.

Input Source

ATV, AV, Component (480i, 480p)
DTV (HDMI, 1080p), Component (1080i, 1080p), HDMI (720p, 1080i, 1080p)

Picture Size

16:9, Zoom
Zoom: 4:3
16:9, Wide Fit
4:3, Screen Fit

Digital Clean View (Off / Low / Medium / High / Auto) /

Reduces the signal received by your TV is weak, you can activate the Digital Clean View feature to reduce any static and ghosting that may appear on the screen.
When the signal is weak, try all the Digital Clean View options until the TV displays the best picture.
MPEG Noise Filter (Off / Low / Medium / High / Auto): Reduces MPEG noise to provide improved picture quality.
HDMI Black Level (Normal / Low): For HDMI signals, select the black level to adjust the screen depth. Low make blacks look darker.
Available only in HDMI mode (RGB signals).

Film Mode (Off / Auto / Auto2)

Sets the TV to automatically sense and process film signals from all sources and adjusts the picture for optimum quality.
Available in ATV, DTV (interlaced), AV, COMPONENT (480i / 1080i) and HDMI (480i / 1080p).

LED Rear Motion (Off / On)

Removes drag from fast scenes with a bit of momentum to provide a clear picture.

Picture Reset

Picture Reset (Reset Picture Mode/Cancel): Resets the picture settings to their factory defaults.

Sound Menu

Mode: Selects the normal sound mode.
Music: Emphasizes bass notes.
Movie: Provides the best sound for movies.
Clear Voice: Emphasizes voices over other sounds.
Amplify: Increase the intensity of high-frequency sounds to allow a better listening experience for the hearing impaired.

Equalizer

Balance L/R: Adjusts the balance between the right and left channels.
100Hz / 300Hz / 1KHz / 30KHz / 10KHz (Bandwidth Adjustment): Adjusts the loudness of specific bandwidth frequencies.
Reset: Resets the equalizer to its default settings.

SRS TruSurround HD (On/Off)

Available in Standard sound mode only.
SRS TruSurround HD is a patented SRS technology that solves the problem of playing 5.1 multichannel content through two speakers. TruSurround delivers a compelling, virtual surround sound experience through any two-speaker playback system, including in-ear television speakers. It is fully compatible with all multichannel formats.
When the TV is connected to a PC, you can only make changes to the Color Tone, Size and HDMI Black Level.
Input Source are listed below.

Preferred Language

Digital-TV broadcasts can transmit many audio tracks simultaneously (for example, simultaneous translations of a program into foreign languages).
You can only select a language from among the ones being broadcast.

Multi-Track Sound (MTS)

Analog channels only.
Mono: Select for channels that are broadcasting in mono or if you are having difficulty receiving a stereo signal.
Stereo: Select for channels that are broadcasting in stereo.
SAP: Select to listen to the Separate Audio Program, which is usually a foreign language translation.
Depending on the program being broadcast, you can listen to Mono, Stereo or SAP.

Auto Volume

Automatically adjusts the volume level when you change video sources or content so the level remains the same.

Sound Reset

Reset All: Resets all sound settings to the factory defaults.

Channel Menu

Memorizing Channels
When you first set up your TV using Plug & Play, the TV memorized the channels that were available over the air or through your cable system and added them to the Channel List. The Antenna and Auto Program functions described below let you run the channel memorization function without having to re-run the Plug & Play procedure.

Antenna (Air / Cable)

Before your television can memorize the available channels, you must first select your TV's signal source. Air (using an antenna) or Cable. Select Menu > Channel > Antenna > Air or Cable. After you have selected the signal source, go on to the Auto Program function.

Selecting the signal source using the Antenna function also determines the signal source the TV is tuned to. For example, if you receive your TV signal over the air, and you select Cable, you will see no picture. You must select Air to see a picture.

Auto Program

The Auto Program function memorizes all channels that are available over the air or through your cable system and adds them to the Channel List.

To start Auto Program, follow these steps:

- 1. Push MENU/EXIT --> Channel --> Auto Program --> ENTER on your remote. The Antenna Source screen appears.
2. On the Antenna Source screen, select the source of your TV signal.

Air

If your TV is connected to an antenna choose Air, and then press ENTER on the TV. The TV will automatically start memorizing channels.

Cable

If your TV is connected to a cable outlet, choose Cable, and then press ENTER on the TV. Go to Step 3.

Game Mode (On/Off)

When you connect a game console such as a PlayStation 3 or Xbox 360 to your TV, you can enjoy a more realistic gaming experience by turning on the Game Mode function.

Precautions and limitations for game mode:
Before you disconnect the game console and connect another external device, set Game Mode to Off in the setup menu.
If you display the TV menu in Game Mode, the screen shakes slightly.
Game Mode is not available when the input source is set to TV.
After connecting the game console, set Game Mode to On. You may notice slightly reduced picture quality.

Caption

On-Screen Text Dialogue
Caption: You can switch the caption function on or off. If captions are not available, they will not be displayed on the screen.
The Caption feature does not work in Component or HDMI mode.
Caption Mode: You can select the desired caption mode.
Default / CCI- / CCA / Text1 - Text4: (analog channels only) The Analog Caption function operates in either analog TV channel mode when a signal is applied from an external device to the TV. (Depending on the broadcasting signal, the Analog Caption function may or may not work with digital channels.)
Default / Service1 - Service / CCI- / CCA / Text1 - Text4: (digital channels only) The Digital Captions function works with digital channels.
Service: 6 may not be available in digital caption mode depending on the broadcast.
Digital Caption Options: (Digital channels only)
Size: Options include Default, Small, Standard and Large. The default is Standard.
Font Style: Options include Default and Styles 0 to 7. The default is Style 0.
Background Color: Options include Default, White, Black, Red, Green, Blue, Yellow, Magenta and Cyan. You can change the color of the letters. The default is White.
Background Opacity: This adjusts the opacity of the caption background. Options include Default, Transparent, Translucent, Solid and Flashing.
Return to Default: This option sets each Size, Font Style, Background Color, Background Color, Foreground Opacity and Background Opacity to its default.

Digital Caption Options are available only when you can select Default and Service - Service6 in Caption Mode. The Foreground and Background cannot be set to the same color.

Melody

Set so that a melody plays when the TV is turned on or off.
The Melody does not play:
When no sound is output from the TV because the MUTE button has been pressed.
When no sound is output from the TV because the volume has been reduced to minimum with the VOL - button.
When the TV is turned off by Sleep Timer function.

Auto

If you choose Auto, and then press ENTER on the TV, the TV will automatically select the correct Antenna source. Go to Step 3.

On the Cable Type screen, use the Arrow buttons to select the type of digital and analog cable systems you have. STD, HRC, or HRC. Most systems are STD (Standard). When done, select Start, and then press ENTER on the TV. The TV will start memorizing channels.

Channel memorization can take up to 45 minutes, depending on your cable system.

Memorized channels are added to the Added Channels list. These are the channels you will see when you use the Channel buttons on your remote.

Clear Scrambled Channel

This function filters out scrambled channels after Auto Program is completed. This process may take up to 20-30 minutes.

Press the ENTER button to stop the Clear Scrambled Channel.

This function is only available in Cable mode.

Managing Channels

Channel List

See your list of Added Channels, Favorite channels, or channels you're scheduled for viewing. Add or delete Favorite channels, add or delete channels from the Added Channels list, schedule channels or programs for viewing. Watch a channel by selecting the channel in the All Channels, Added Channels, or Favorites screen, pressing the Arrow buttons, and then pressing the ENTER button.

All deleted channels will be shown on the All Channels list. You add channels back to the Added Channels list on the All Channels list.

A Gray-colored channel indicates the channel has been deleted from the Added Channels list.

The Add menu option only appears for deleted channels.

Add to Favorite/Delete from Favorite: Lets you add channels to and delete channels from your Favorites list.

To add channels to the Favorites list, follow these steps:

- 1. Select one or more channels in the All Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Add to Favorite in the Tools menu, and then press the ENTER button.

To delete channels from the Favorites list, follow these steps:

- 1. Select one or more channels in the Favorites Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Delete from Favorite in the Tools menu, and then press the ENTER button.

To delete channels from the Favorites list, follow these steps:

- 1. Select one or more channels in the Favorites Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Delete from Favorite in the Tools menu, and then press the ENTER button.

Remote control buttons actuated on the Channel List screen:
Green Zoom: Enlarges or shrinks a channel number.
Color Select: Move the cursor to a channel. Press the Yellow button to select the channel. A mark appears. Repeat to select other channels. Then, push the Tools menu and apply a function to the channels you selected.
Add Tools: Displays the Channel List Tools menu. (The Tools menu may differ depending on the situation.)

Channel List Screens icons are listed on the left side. Select an icon using the Arrow buttons to view each list.

All Channels: Shows all currently available channels including those you deleted from the Added Channels list.
Added Channels: Shows all Added Channels. These are the channels that appear when you press the CH button.
Favorite Channels: Shows all favorite channels.
Programmed: Shows all channels and programs currently scheduled for viewing using Time Viewing.

Auto Protection Time

Auto Protection Time (Off / 2 hours / 4 hours / 8 hours / 10 hours): If the screen remains idle with a still image for a certain period of time you desire, the screen saver is activated to prevent the formation of ghost images on the screen.

Eco Solution

Energy Saving (Off / Low / Medium / High / Picture Off): The screen Selects: Move the cursor to a channel. Press the Yellow button to select the channel. A mark appears. Repeat to select other channels. Then, push the Tools menu and apply a function to the channels you selected.

No Signal Power Off (Off / 15 min. / 30 min. / 60 min.): Sets how long the TV switches to standby mode, if no picture is being received.

Disabled when the PC is in power saving mode.

Auto Power Off (Off / On): The TV will automatically turned off when no user operation is received for 4 hours.

Support Menu

Self Diagnosis

Picture Test: Used to check for picture problems. If the problem appears in the test picture, select Yes and follow the directions on the screen.

Sound Test: Use the built-in melody sound to check for sound problems. If the problem occurs during the test, select Yes and follow the directions on the screen.

Signal Strength: (Digital channels only) An HD channel's reception quality is either perfect or the channels are unavailable. Adjust your antenna to increase signal strength.

Reset: Reset all settings to the factory defaults.
The PIN input screen appears before the setup screen.
Enter your 4-digit PIN. Change the PIN using the Change PIN option.

Software Upgrade

Software Upgrade can be performed by downloading the latest firmware from samsung.com to a USB memory device.

HD Connection Guide

Refer to this information when connecting external devices to the TV.

Contact Samsung

View the information when your TV does not work properly or when you want to upgrade the software. You can find information regarding our call centers and how to download products and software.

Media Play

Enjoy photos, music and/or movie files when you run Media Play. To use the remote the Remote Play function on the PC to permanently delete the file.

Photos only supports the sequential jpeg format.

The Videos option does not support the scene search and track recording.

If the number of files and folders saved on a USB storage device is over approximately 4000, the files and folders may not appear and some folders may not open.

Display Icons Used in the Channel List Screens

Table with 2 columns: Icons and Meaning. Rows for Favorite channel, Reserved program, and Program currently being broadcast.

The Channel List Tools Menu

The Channel List Tools menu contains most of the functions you can use on the Channel List, Added Channel and Favorites List screens. To view, select a list screen, select a channel, and then press the TOOLS button.

Add / Delete: Delete a channel from or add a channel to the Added Channels list.

To delete channels from the Added Channels list, follow these steps:

- 1. Select one or more channels in the Added Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Delete in the Tools menu, and then press the ENTER button.

To add channels to the Added Channels list, follow these steps:

- 1. Select one or more channels in the All Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Add in the Tools menu, and then press the ENTER button.

All deleted channels will be shown on the All Channels list. You add channels back to the Added Channels list on the All Channels list.

A Gray-colored channel indicates the channel has been deleted from the Added Channels list.

The Add menu option only appears for deleted channels.

Add to Favorite/Delete from Favorite: Lets you add channels to and delete channels from your Favorites list.

To add channels to the Favorites list, follow these steps:

- 1. Select one or more channels in the All Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Add to Favorite in the Tools menu, and then press the ENTER button.

To delete channels from the Favorites list, follow these steps:

- 1. Select one or more channels in the Favorites Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Delete from Favorite in the Tools menu, and then press the ENTER button.

To delete channels from the Favorites list, follow these steps:

- 1. Select one or more channels in the Favorites Channels list using the Arrow buttons and the Yellow Select button on your remote.
2. Press the TOOLS button on your remote. The Tools menu appears.
3. Select Delete from Favorite in the Tools menu, and then press the ENTER button.

Remote control buttons actuated on the Channel List screen:
Green Zoom: Enlarges or shrinks a channel number.
Color Select: Move the cursor to a channel. Press the Yellow button to select the channel. A mark appears. Repeat to select other channels. Then, push the Tools menu and apply a function to the channels you selected.
Add Tools: Displays the Channel List Tools menu. (The Tools menu may differ depending on the situation.)

Using

- The maximum displayed number of files, including sub folders, in one folder of USB storage device is 2000.
- The media may not be playing smoothly when using the device lower than USB 2.0.

Videos



- In the **Media Play** menu, press the **Left Arrow** button to select **Videos**, and then press the **ENTER** button.
- Press the **Left Arrow** buttons to select a video in the file list.
- Press the **ENTER** button or **Play** button.

- The file name information is unknown, playing time and the progress bar are not displayed.
- During video playback, you can search using the **Left Arrow** and **Right Arrow** buttons.

In this mode, you can play movie clips contained in a game, but you cannot play the game itself.

Supported Video Formats

File Extension	Container	Video Codec	Resolution	Frame rate/frame/s	Bit rate/KB/s	Audio Codec
.avi	AVI	DivX 5.11.4.5.6		30		AC3
.wmv	WMV	MPEG4 SP	1920x1080			AC3
.mp4	MPEG4	MPEG4 SP / ASP				AC3
.h264	H.264	H.264 SP / MP / AP				AC3
.m2ts	MPEG2	MPEG2	544x630	6-30		AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3
.m2t	MPEG2	MPEG2				AC3
.m2ts	MPEG2	MPEG2				AC3
.m2p	MPEG2	MPEG2				AC3